




**Intech microwaves s.r.l.**

Sede Legale e Operativa: Via Giacomo Peroni 400, 00131 Roma (RM) – Italy  
Cap. Soc. € 80.000,00 – P.IVA 12934711008 – REA RM1411466  
Tel: +39 06 4568 3104 - Email : info@intech-mw.com PEC: intech.microwaves@pec.it

## X-Band 4 Way Combiner MODEL AXXXXXX

### **Features:**

- ❖ HPA Applications
- ❖ TWT Replacement
- ❖ Instantaneous 2000 MHz bandwidth
- ❖ Wave Guide Technology
- ❖ Ideal Building Block for solid state High Power Amplifier



### **Performance Specifications**

- ❖ Frequency Range: 8 to 10 GHz
- ❖ Power Handling: 3 kW peak (+64.8 dBm)
- ❖ Insertion Loss: 0.3 dB nominal
- ❖ Input VSWR: <1.21:1
- ❖ Output Load VSWR: <1.21:1

- ❖ RF Connectors:
  - RF Input Port: RWG WR90
  - RF Output: RWG WR90

Intech Microwaves introduces a Wave Guide Power Combiner. This design operates over the full 8-10 GHz frequency range and is ideal as Building Block for solid state High power Amplifier. Contact our Marketing or local Representatives to discuss how IMW experts can support you with its standard or custom designs for L, S, C, and X Band Pulse Radar, TWT replacement, IFF, EW Jamming, Satellite, or Medical Instrumentation.